



## 12V DC to AC 750 Watt Power Inverter



Patent Pending

This inverter plugs into your cigarette lighter or directly to a 12 Volt DC battery to power laptops, cell phone chargers and other small electronic devices in your vehicle!

### Features:

- 750 watts continuous power
- 1500 watts peak power
- Provides 6.3 Amps
- Built-in Cooling Fan
- 120 volt AC outlets
- Overload Indicator
- Power ON/OFF Switch
- USB Charging Port

### Accessories Included:

- Battery Clip Cables



Intertek  
3149458

Output Wave Form	Modified Sinewave
No-load draw	< 0.16 amp (12V)
Efficiency	Up to 90%
Input voltage range	10-15 VDC
Over voltage shutdown	over 15 VDC
Under voltage shutdown	under 10 VDC
Low voltage alarm	Audible at 10.6 VDC
Overload shutdown	Yes
Thermal shutdown	Yes
Short circuit shutdown	Yes
AC receptacle	Two 3-Prong
Warranty	2 year
Inverter weight	2.6 lbs
Dimensions (W x H x D)	7.5 x 2.5 x 6 in.